

# LEMO 45BC-12<sup>2</sup>



Connection: Traditional Power Supply (200 V/LEMO)  
Channel(s): 2  
Standards: ANSI: S3.36  
Based on IEC 60318-4 and 60318-7  
Based on ITU-T Rec. P.57 Type 3.3 and ITU-T Rec. P.58  
Special feature: Built-in power amplifier for mouth simulator

45BC-12 KEMAR

1 LEMO

[GRAS 45BC-11 KEMAR](#)

## Introduction

The KEMAR head and torso simulator was introduced by Knowles in 1972 and quickly became the industry standard for hearing-aid manufacturers and research audiologists (visit [KEMAR.us](https://www.kemar.us) to read the full story). It is based on worldwide average human male and female head and torso dimensions. It meets the requirements of ANSI S3.36/ASA58-2012 and IEC 60318-7:2011.

The current KEMAR Head and Torso has the same dimensions and acoustical properties as the original KEMAR, but has been developed further by GRAS to meet the industry's demand for realistic measurements of hearing aids, headphones and headsets. It provides acoustic diffraction similar to that encountered around the median human head and torso, both in the proximity and in the far-field.

As all the preconfigured 45BC KEMARs consist of the same basic 45BC KEMAR Non-configured, plus a set of application-specific accessories, the full information about a given KEMAR configuration is obtained by combining the information about the 45BC KEMAR Non-configured and the information for a given configured version as found in the present text. Read about the non-configured KEMAR [here](#).

## Design

The 45BC-12 is a KEMAR with mouth simulator, anthropometric pinnae and low-noise ear simulators for 2-channel low-noise headset test. It is delivered fully configured, individually calibrated and ready for use. In addition to a system calibration certificate, a USB flash memory with simulation data is included.

The accessories specific for this configuration are listed in the Ordering Info tab.

The main configuration specific components of the 45BC-12 are the GRAS 44AA Mouth Simulator, the

GRAS 43BB Low-noise Ear Simulator System and the KB5000/KB5001 anthropometric pinnae.

*The 44AA Mouth Simulator according to ITU-T Rec. P51 with built-in power amplifier*

The maximum continuous signal the mouth can produce in 1/3-octave bands is 100dB re. 20μPa in the frequency range of 100Hz to 16kHz. Its loudspeaker accepts an external signal either directly or via its own built-in power amplifier (when power is applied).

*The 43BB Low-noise Ear Simulator System*

Basically the 43BB consists of an IEC 60318-4 Ear Simulator and a 40HT Low-noise Microphone System.

The built-in microphone is the 40AH Low-noise Ext. Polarized Pressure Microphone has a specially reduced noise floor in order to achieve a large dynamic range.

Below 10 kHz, the frequency response is identical to that of a standard IEC 60318-4 ear simulator. Above 10 kHz, the differences in the microphone diaphragm impedance result in substantial differences. The standard ear simulator has a high-Q resonance of around 13.5 kHz related to the length of the ear canal and the diaphragm impedance. In the low noise version of the ear simulator the single high-Q resonance is replaced by two resonances. Part of the design of the low noise microphone is a filter unit that controls the mechanical resonance of the low noise microphone. The combination of the filter and the low damping of the diaphragm cancels out the high peak of the resonance in the simulator.

The preamplifier is the 26HG which is similar to the GRAS 26AC ¼" Standard Preamplifier, but with a 40 G input impedance to enable low-level noise measurements. It has an integrated lightweight

cable terminated in a 7-pin LEMO connector that plugs into the 26HT Gain and Filter Unit.

To complete the system, a special power module is part of the delivery, i.e. the 12HF 1-Channel Power Module for Low-noise Systems.

Read more about the [43BB Low-noise Ear Simulator System](#).

### *The Anthropometric Pinna*

Compared to the standardized pinna, the anthropometric pinna embodies a number of improvements to the concha and ear canal, combined with increased collapsibility of the helix, and improved mounting. It is made of soft silicone, 35 Shore 00 hardness.

The external shape of the pinna is identical to that of the standardized KEMAR pinna, but concha and ear canal have been modified so that they closely mimic the properties of a real human ear. The ear canal has been extended and is now an integral part of the pinna, which seals directly against the ear simulator. Like the human ear, the ear canal has the 1st and 2nd bend, and the interface with the concha is oval. Fit and insertion consistency are much improved over the cylindrically or conically shaped ear canal extensions that are used with the standard pinna.

The flexibility of the outer ear has been improved, and when mounting supra-aural and circum-aural headphones the pinna now collapses against the head very much like a human ear.

In addition to the traditional push mounting from the outside, the pinna is secured with two screws from the inside of KEMAR's head. These two screws ensure that the pinna is held firmly in place. Therefore, it seals perfectly against the ear simulator and the head, and it is, therefore, possible to mount and dismount DUTs repeatedly without

compromising the seal.

Read more about the [Anthropometric Pinnae](#).

## Typical Applications

45BC-12 is configured to meet the consumer electronics industry's need for R&D testing of headsets, including sets with Active Noise Cancellation.

The anatomical shape of the pinnae makes it possible to achieve an excellent fit and sealing with anatomically shaped in-ear transducers. Controlling the insertion depth is easy, leading to good insertion consistency and highly improved repeatability and accuracy of measurements. The improved fit and seal also means that the low-frequency response is improved. It will allow you to reproduce bass notes, as well as effectively measure (active & passive) attenuation.

Because it can measure down to and below the threshold of human hearing, it can measure the influence of the electronics on the audio response of the earphones. Its low noise floor and usability above 10 kHz means that measurement results will have a strong correlation with the subjective feedback from test persons and users.

The low inherent noise of the system also means that THD and Rub & Buzz at very low levels can be investigated. The improved collapsibility of the pinna and the built-in mouth simulator make it well suited for testing of supra-aural and circumaural headsets.

## Performance and warranty

KEMAR is made of components from our standard portfolio, all manufactured of high-quality material and branded parts that were chosen and processed to ensure life-long stability and robustness. This enables us to offer 2 years warranty against defective materials and workmanship.

Exceptions: Microphones included in KEMAR as for these our normal 5-year warranty apply. The warranty period for cables is 6 months.



|  |   |                        |
|--|---|------------------------|
| Set sensitivity @ 250 Hz ( $\pm 2$ dB)   | mV/Pa                                   | 800                    |
| Theoretical dynamic range lower limit with GRAS preamplifier                                   | dB(A)                                   | 10.5                   |
| Theoretical dynamic range upper limit with GRAS preamplifier @ +28 V / $\pm 14$ V power supply | dB                                      | 113                    |
| Temperature range, operation   | $^{\circ}\text{C}$ / $^{\circ}\text{F}$ | -30 to 60 / -22 to 140 |
| Temperature range, storage   | $^{\circ}\text{C}$ / $^{\circ}\text{F}$ | -40 to 65 / -40 to 149 |
| Humidity range non condensing  | % RH                                    | 0 to 95%               |
| ANSI standard  |   | S3.36                  |
| IEC standard   |   | 60318-7                |
| ITU-T recommendations  |   | P. 58                  |
| Weight   | g / oz                                  | 11.45 k / 404          |
| MOUTH SIMULATOR  |   | .                      |
| Output impedance   | $\Omega$                                | 8                      |
| Maximum power, continuous  | W                                       | 10                     |
| Maximum power, pulsed 2 sec.   | W                                       | 50                     |
| Input impedance  | k                                       | 20                     |
| Gain   | dB                                      | 10                     |
| Input signal, max.   | V <sub>rms</sub>                        | 2                      |
| Power supply, external   | V <sub>dc</sub>                         | 24                     |

GRAS Sound & Vibration reserves the right to change specifications and accessories without notice.

## Included items

|                             |  |
|-----------------------------|--|
| <a href="#">GRAS 45BC</a>   | KEMAR Head & Torso with <a href="#">GRAS 44AA Mouth Simulator</a> , Non-configured |
| <a href="#">GRAS KB5000</a> | Large Right Anthropometric Pinna 35 Shore 00                                       |
| <a href="#">GRAS KB5001</a> | Large Left Anthropometric Pinna 35 Shore 00  |
| GRAS GR1874                 | Ear Simulator Holder (2 pcs)   |
| GRAS GR0408                 | External Ear Canal (2 pcs)   |
| GRAS GR0409                 | Union Nut (2 pcs)  |
| <a href="#">GRAS AA0035</a> | BNC-BNC cable, 3 m   |
| <a href="#">GRAS 46BD</a>   | 1/4" CCP Pressure Standard Microphone Set (for mouth calibration)                  |
| <a href="#">GRAS 43BB-1</a> | Low-noise Ear Simulator System, 2 pcs, each comprising:                            |
| <a href="#">GRAS RA0001</a> | Right Angled Adapter for 1/2" Microphone and 1/4" Preamplifier                     |
| GRAS RA0234                 | Low-noise Ear Simulator  |
| GRAS 26HG-S1                | 1/4" Preamplifier with 0.4 m Integrated Cable                                      |
| GRAS 26HT                   | Gain and Filter Unit for 40HT  |
| <a href="#">GRAS 12HF</a>   | 1-Channel Power Module for Low-noise Systems                                       |
| GRAS AA0059                 | LEMO cable for low-noise system  |
| <a href="#">GRAS AA0035</a> | BNC-BNC cable, 3 m   |

## Optional items

### For Ear Simulator Calibration

|                             |  |
|-----------------------------|--|
| <a href="#">GRAS 42AP</a>   | Intelligent Pistonphone (250 Hz or 251.2 Hz, 114 dB +/- 0.05 dB) |
| <a href="#">GRAS 42AA</a>   | Pistonphone (250 Hz, 114 dB +/- 0.08 dB)                         |
| <a href="#">GRAS RA0090</a> | 94 dB Pistonphone Coupler  |

### Pinna Simulators

|                             |                                   |
|-----------------------------|-----------------------------------|
| <a href="#">GRAS KB0060</a> | KEMAR Small Right Ear 55 Shore 00 |
| <a href="#">GRAS KB0061</a> | KEMAR Small Left Ear 55 Shore 00  |

|                             |   |
|-----------------------------|---|
| <a href="#">GRAS KB0065</a> | KEMAR Large Right Ear 55 Shore 00               |
| <a href="#">GRAS KB0066</a> | KEMAR Large Left Ear 55 Shore 00                |
| <a href="#">GRAS KB1060</a> | KEMAR Small Right Ear, 35 Shore 00              |
| <a href="#">GRAS KB1061</a> | KEMAR Small Left Ear 35 Shore 00                |
| <a href="#">GRAS KB1065</a> | KEMAR Large Right Ear 35 Shore 00               |
| <a href="#">GRAS KB1066</a> | KEMAR Large Left Ear 35 Shore 00                |
| <a href="#">GRAS KB0090</a> | KEMAR Large Right Ear (VA-Style/SQ) 55 Shore 00 |
| <a href="#">GRAS KB0091</a> | KEMAR Large Left Ear (VA-Style/SQ) 55 Shore 00  |
| <a href="#">GRAS KB1090</a> | KEMAR Large Right Ear (VA-Style) 35 Shore 00    |
| <a href="#">GRAS KB1091</a> | KEMAR Large Left Ear (VA-Style) 35 Shore 00     |

## Ear Mould Simulators

|                             |  |
|-----------------------------|--|
| <a href="#">GRAS KB0110</a> | Ear Mould Simulator for 2 mm Inner diameter tubing |
| <a href="#">GRAS KB0111</a> | Ear Mould Simulator for 3 mm Inner diameter tubing |

## Ear Canal Extension and Microphone Holder Kits (kits with 2 pcs and O-rings)

|                             |  |
|-----------------------------|--|
| <a href="#">GRAS RA0237</a> | Straight Ear Canal Extension Kit for KEMAR   |
| <a href="#">GRAS RA0238</a> | VA-tapered Ear Canal Extension Kit for KEMAR   |
| <a href="#">GRAS RA0239</a> | Ear canal Extension Kit w. silicone lining for KEMAR                                   |
| <a href="#">GRAS RA0240</a> | Holder for long 1/2" microphone Kit for KEMAR  |
| <a href="#">GRAS RA0241</a> | Holder for short 1/2" microphone Kit for KEMAR   |
| <a href="#">GRAS RA0243</a> | Holder for 1/2" microphone Kit for KEMAR   |
| <a href="#">GRAS RA0244</a> | O-ring kit for KEMAR, 2 pcs.   |
| <a href="#">GRAS RA0249</a> | Straight Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test |
| <a href="#">GRAS RA0250</a> | Tapered Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test  |

## KEMAR Retrofit Kit for Binaural Hearing Aid Test

[GRAS RA0251](#)

KEMAR Retrofit Kit for Binaural Hearing Aid Test:  
The Kit includes Ear Holder Plates, mounting bolts and the RA0249 and RA0250 Ear Canal Extension Kits. Included items are made of POM, Nylon and Teflon.

## Cables

[GRAS AA0046](#)

3 m LEMO 7-pin - LEMO 7-pin Cable for Low-noise measuring system

[GRAS AA0047](#)

10 m LEMO 7-pin - LEMO 7-pin Cable for Low-noise measuring system

## Flight Case

GRAS KM0094

PELI Case for KEMAR

## Simulation Model of KEMAR

GRAS KB3000

Simulation Model of KEMAR with large pinnae

GRAS KB3001

Simulation Model of KEMAR with small pinnae

## Stand for KEMAR

GRAS AL0026

Loudspeaker stand for KEMAR, Ø 35 mm

## Miscellaneous

GRAS KB0000

KEMAR Handbook

GRAS KB0010

T-Shirt for KEMAR

GRAS Sound & Vibration reserves the right to change accessories without notice.

# GRAS Worldwide

Subsidiaries and distributors in more  
than 40 countries

**HEAD OFFICE, DENMARK**  
**GRAS SOUND & VIBRATION**  
Skovlytoften 33  
2840 Holte  
Denmark  
Tel: +45 4566 4046  
[www.GRASacoustics.com](http://www.GRASacoustics.com)  
[gras@grasacoustics.com](mailto:gras@grasacoustics.com)

**USA**  
**GRAS SOUND & VIBRATION**  
9290 SW Nimbus Avenue  
Beaverton, OR 97008  
Tel: 503-627-0832  
Toll Free: 800-231-7350  
[www.GRASacoustics.com](http://www.GRASacoustics.com)  
[sales-usa@grasacoustics.com](mailto:sales-usa@grasacoustics.com)

**UK**  
**GRAS SOUND & VIBRATION**  
Unit 115, Gibson House,  
Ermine Business Park, Huntingdon,  
Cambridgeshire, PE29 6XU  
Tel: +44 (0) 7762 584 202  
[www.GRASacoustics.com](http://www.GRASacoustics.com)  
[sales-uk@grasacoustics.com](mailto:sales-uk@grasacoustics.com)

**CHINA**  
**GRAS SOUND & VIBRATION**  
Room 315, RuiBo Center(T1)  
Lane683, Shenhong Rd,  
Minhang District,  
Shanghai, China, 201107  
Tel: +86 21 64203370  
[www.GRASacoustics.cn](http://www.GRASacoustics.cn)  
[cnsales@grasacoustics.com](mailto:cnsales@grasacoustics.com)



## About GRAS Sound & Vibration

GRAS is a worldwide leader in the sound and vibration industry. We develop and manufacture state-of-the-art measurement microphones and related equipment for industries where acoustic measuring accuracy and repeatability are of the utmost importance. This includes applications and solutions for customers within the fields of aerospace, automotive, audiology, consumer electronics and other highly demanding industries. GRAS microphones are designed to live up to the high quality, durability and accuracy that our customers have come to expect, trust and require.

GRAS Sound & Vibration is represented through subsidiaries and distributors in more than 40 countries and is part of Axiometrix Solutions, a leading test solutions provider comprised of globally recognized measurement brands. Read more at [www.grasacoustics.com](http://www.grasacoustics.com)

[grasacoustics.com](http://grasacoustics.com)

**GRAS**  
An Axiometrix Solutions Brand